- 1. Dôležité: Musíte byť pripojený na router ktorý chcete upgradnuť, buď cez wifi alebo cez kábel.
- 2. Otvorte WEB prehliadač (Chrome, Firefox, Edge...)
- 3. Zadajte adresu 192.168.0.1

← → C ⋒ ▲ Nezabezpečené 192.168.0.1		©7
Ptp-link   Archer C80		
a second to the second		
	Log In with Local Password	
	Local Password:	
	LOG IN Forgot Password?	

4. Zadajte heslo (Local Password) admin1234

Log In with Local Password
Local Password:
admin1234 O
LOG IN
Forgot Password?
💪 Log In with TP-Link ID

5. Kliknite na **Advance** 

Archer C80		Q Search	🕹 TP-Link ID	🕞 Log Out	
 Network Map	Internet	Wireless	Advanced		
Internet	2.46 56 ⇒   ≑ ⇒   ÷	Mesh Devices		2 Clients	
Internet Status					
Connection Type: WAN MAC Address:	Dynamic IP 00-31-92-84-73-BA	Internet IP Address:		100.72.113.96	

6. Vyberte položku System a potom Firmware Update

			$\overline{\bigcirc}$			
			(?)	<u></u>		
	Network Map	Internet	Wireless	Advanced		
Quick Setup	Operation Mo	de				
Operation Mode	Select an operat	ion mode according to y	/our needs.			
Network	Router Mor	de (Current)				
TP-Link ID	In this mode	e the router can provide	internet access for multiple	wired and wireless de	ovices This mode	
EasyMesh	is required i	most commonly.	memer access for multiple	when and whereas de	evices. This mode	
Wireless			))	((1-		
NAT Forwarding		₩.			E	
Parental Controls		τ	, C			
QoS						
Security	Access Poi	int Mode				
IPv6	In this mode	e, the router changes ar	existing wired network into	a wireless one.		
Smart Life Assistant			internet LAN	*) (¢	Ē	
System		۲		•		

7. Nastavte **Auto Update**. Nižšie vidíte: **Latest Firmware Version**: 1.13.15 Build 240812 Rel.53634n(4555) -> Posledná verzia. Pre upgrade kliknite na **UPDATE** 

	Notwork Man	Internet	Mérologo	Advanced		
	Network map	Internet	WIEless	Auvanceu		
<ul> <li>Quick Setup</li> </ul>	Auto Update					
Operation Mode	Update firmwar	e automatically when ne	v version is available.			
Network		Auto Hadata				
TP-Link ID		Auto Opdate.	2025 04 02 02 54 42	Setting		
EasyMesh		Undata Timo:	02:00 05:00	Joening		
Wireless		Opdate Time.	Note: If the router detects a	nyone is using the i	nternet at the	
NAT Forwarding			time, the update will be res	cheduled for the nex	d day.	
Parental Controls	Online Updat	le				
QoS	Update firmwar	e over the internet.				
Security						
IPv6		Firmware Version:	1.13.2 Build 230824 Rel.747	02n(4555)		
Smart Life Assistant		Hardware Version:	Archer C80 1.0			
System	L	atest Firmware Version:	1.13.15 Build 240812 Rel.53	634n(4555) What's	New	
Firmware Update			UPDATE			_
Backup & Restore						_
Administration	Local Update	•				
System Log	Update firmwar	e from a local file.				
CWMP Settings		New Firmers File				
Diagnostics		wew Firmware File.	PROWEE			
Time & Language			BROWSE			
Reboot			UPDATE			
LED Control						
	EasyMesh Sa	atellite Update				
	Update firmwar	e for TP-Link EasyMesh	satellite routers over the interr	iet.		
	Type De	evice Name Model	Firmware Version	Latest Firmwa	re Update	
	.,,			Version		

## 8. Kliknite na **UPDATE**

EasyMesh	Lindate Time:	03.00 - 05.00
Wireless		Note: If the router detects anyone is using the internet at the
NAT Forwarding		time, the update will be reschedured for the next day.
Parental Controls	Online Undate	
QoS	Update firmware over the internet.	
Security		
IPv6		×
Smart Life	The update will take a few minutes and the router in	vil reboot. Update now?
Satan		CANCEL UPDATE
System	L	
Firmware Update		UPDATE
Backup & Restore		
	Local Hedete	

	Update firmware over the internet.	
		_
		200/
	Downloading	50%
•	UPDATE	

	Update firmware over the internet.		
ſ		37%	
ł	Rebooting		
	UPDATE		

- 9. Toto je všetko.
- 10. Doporučené nastavenia pre WIFI: **Smart Connect** -> Neoznačené, **Channel With** 2.4 GHz -> 40MHz a 5G -> 80 MHz

CPRINK T Archer C8			C Search	• TP-Link	io 🕒 Log Out	•
	<b>(A)</b>	۲	1	0		
	Network Map	Internet	Wireless	Advanced		
Quick Setup	Wireless Settin	gs				
Operation Mode	Personalize wirele	s settings as you ne	<b>1</b> .]			
Network		Smart Connect	Enable 🕜			
TP-Link ID		2.4 GHz	Enable		Share Network	
EasyMesh	N	etwork Name (SSID):	TP-Link_		Hide SSID	
Wireless		Security:	WPA2-PSK[AES]	~		
Wireless Settings		Password:				
Guest Network		Transmit Power:	High	~		
IoT Network		Channel Width	40 MHz	~		
Wireless Schedule		Channel	Auto			
WPS		Mada	002 titles mixed	*		
Additional Settings		Mode.	802. Horgin mixed	~		
WDS		5 GHz	Enable		Share Network	
NAT Forwarding	N	etwork Name (SSID):	TP-Link5G		Hide SSID	
Parental Controls		Security:	WPA2-PSK[AES]	~		
QoS		Password:				
Security		Transmit Power:	High	~		
IPv6		Channel Width:	80 MHz	~		
Smart Life		Channel	Auto	~		
Assistant		Mode	802.11a/n/ac mixed	~		
System		02100000				

## 11. Channel -> Vyberte ľubovoľne číslo

	Network Map	Internet	Wireless	Advanced		
Quist Ostur	Wireloog Setti	100				
Quick Setup	Percepalize wirel	igs	d			
peration Mode		ess settings as you nee	-u.			
letwork		Smart Connect:	🗌 Enable 🕜			
P-Link ID		2.4 GHz:	Enable		Share Network	
asyMesh	,	letwork Name (SSID):	TP-Link 73B9		Hide SSID	
Vireless		Security				
Wireless Settings		Security.				
Guest Network		Password:	88289595			
InT Natwork		Transmit Power:	High	$\sim$		
		Channel Width:	40 MHz	$\sim$		
wireless Schedule		Channel:	Auto	~		•
WPS		Mode:	Auto			
Additional Settings			1			
WDS		5 GHz:	2		Share Network	
AT Forwarding	1	letwork Name (SSID):	3		Hide SSID	
arental Controls		Security:	4			
00S		Password:	5	J		
ecurity		Transmit Power:	High	~		
2/6		Channel Width:	90 MH7			
				×		
ssistant		Channel:	Auto	Channel:	Auto	~
ystem		Mode:	802.11a/n/ac mixed	Mode:	Auto	
		MU-MIMO:	Enable	VU-MIMO:	40	
					44	
					48	